



## **6ES7223-3BD30-0XB0** S7-1200, SIGNAL BOARD 2DI/2DQ 24V 200KHZ

Technical / CAx data

Technical Data CAx data

## SIMATIC S7-1200, DIGITAL I/O SB 1223, 2DI/2DQ, 24VDC 200KHZ

Supply voltages

Supply Voltages	
Power supply to the transmitters	
Supply current, max.	4 mA; per channel
Current consumption	
from backplane bus 5 V DC, typ.	50 mA
Power losses	
Power loss, typ.	1 W
Digital inputs	
Number of digital inputs	2
in groups of	1
Number of simultaneously controllable inputs	
all mounting positions	
Concurrently controllable inputs, up to 40 ℃	2
Input characteristic curve acc. to IEC 1131, Type 1	Yes
Input voltage	
Rated value, DC	24 V
for signal "0"	0 to 5 V
for signal "1"	15 to 30 V
Input current	
for signal "0", max. (permissible quiescent current)	2 mA
for signal "1", min.	5.8 mA
for signal "1", typ.	14 mA
Input delay (for rated value of input voltage)	
for standard inputs	
parameterizable	Yes; 0.2, 0.4, 0.8, 1.6, 3.2, 6.4, and 12.8 ms, selectable in groups of four
at "0" to "1", max.	2.5 μs
for interrupt inputs	
parameterizable	Yes
for counter/technological functions	
parameterizable	Yes
Cable length	
Cable length, shielded, max.	50 m for technological functions
Digital outputs	
Number of digital outputs	2
in groups of	1
Short-circuit protection of the output	No
Switching capacity of the outputs	
with resistive load, max.	0.1 A

**Output voltage** 

Rated value (DC)	24 V
for signal "0" (DC), max.	0.1 V; with 10k ohms load
for signal "1", min.	20 V
Output current	
for signal "1" rated value	0.1 A
for signal "0" residual current, max.	10 μΑ
Load resistance range	
upper limit	10 Ω
Cable length	
Cable length, shielded, max.	50 m
Interrupts/diagnostics/status information	
Alarms	
Alarms	Yes
Diagnoses	
Diagnostic functions	Yes
Degree of protection	
IP20	Yes
Mechanics	
Plastic	Yes
Dimensions and weight	
Dimensions	
Width	38 mm
Height	62 mm
Depth	21 mm
Weight	
Weight, approx.	40 g
Status	Jun 14, 2010

 $<sup>\</sup>ensuremath{\texttt{©}}$  Siemens AG 2010 - Corporate Information - Privacy Policy - Terms of Use